



### Smart Switch Relay Mechanism

Product Code:  
**KASTA-S350BH-W**

#### APP Installation

Visit [www.kasta.com.au](http://www.kasta.com.au) or your app store to download the free KASTA app.  
iOS: requires iOS 9.0 or later.  
Android: requires Android 4.4 or later.  
Devices must support Bluetooth 4.0



#### Important Safety Information

- This product must be installed by a licensed electrician in accordance with all the requirements of AS/NZS 3000(current edition) and other relevant Standards and Regulations.
  - Electricity **MUST** be disconnected prior to installation. Failure to do so may result in serious injury and or loss of life.
  - Indoor use only. Not suitable for damp or explosive environments.
  - Complies to Australian Standards AS/NZS 60669.2.1, AS/NZS 60669.1, AS/NZS 4268, AS/NZS CISPR 15.
  - No user serviceable parts inside.
  - A load correction device - X2 Capacitor type 275Vac, 0.10µF, 40/110/56/B - has been included with your KASTA Switch Relay.
- If flickering of the luminaire load is experienced, connect the load correction device across the line output of the KASTA Switch Relay to improve performance.

#### FEATURES

- Relay for switching a load on and off.
- Smart functions via phone/tablet with the app such as schedules, timers, scenes and groups.
- Push Button Control.
- Fits most Australian Standard wall mech apertures.
- Simple 2 wire connection-Active in and load out.
- Integral blue backlight that can be enabled/disabled after installation.
- Multi-way load switching possible using KASTA remote switches.
- Built-in thermal current overload protection.

#### FUNCTION SETUP

ON/OFF SWITCH	1 CLICK
Turns lights on or off. When turned ON, lights will adjust to previous brightness setting.	
DELAY TO OFF	3 CLICKS*
Load automatically turns off after set time.	
PAIRING MODE	6 CLICKS
Enter pairing mode for multi-way switching. Lights will pulse.	
BACKLIGHT ON/OFF	7 CLICKS
Disables or enables backlight on button.	
FACTORY RESET	9 CLICKS

Restores all settings back to factory.  
\*If successful, light will pulse the number of times that the switch was clicked, indicating function.

#### TECHNICAL SPECIFICATIONS

- Supply:** 220-240V AC 50Hz
- Operating Temp:** -20°C to 40°C
- LED Load Wattage:** 15W - 350W (Will require "Load Bypass" if less than 15W)  
Small motors such as ceiling exhaust fans Max. 100 W (0.5 A @ 0.8 pf)
- Thermal Derating:** 25°C - 40°C (350W-175W)
- Max Switch Load and Multi Gang:** 350W I 1, 260W I 2, 190W I 3 (Multi Gang Derating on single switch plate)

#### CONNECTION DIAGRAM

