



Battery Powered 5-Button Controller

Product Code:
KASTA-5BCBH-W

APP Installation

Visit www.kasta.com.au or your app store to download the free KASTA app.
iOS: requires iOS 9.0 or later.
Android: requires Android 4.4 or later.
Devices must support Bluetooth 4.0



Important Safety Information

- This product must be installed by a licensed electrician in accordance with all the requirements of AS/NZS 3000 (current edition) and other relevant Standards and Regulations.
- Electricity MUST be disconnected prior to installation. Failure to do so may result in serious injury and or loss of life.
- Indoor use only. Not suitable for damp or explosive environments.
- Complies to Australian Standards AS/NZS 60950.1:2015, AS/NZS CISPR 15.
- No user serviceable parts inside.

FEATURES

- 5 Capacitive Touch Buttons.
- Portable handheld device for easy control.
- Pairs to existing hard wired KASTA devices including: Switch Relays, Dimmers, Curtain controllers and many other devices.
- Configure smart functions via the KASTA app such as timers, scenes and groups.
- Built in magnetic base provides additional mounting options.

FUNCTION SETUP

ON/OFF	1 PRESS
Turns lights on or off. When paired with a dimmable light, light will adjust to previous brightness level.	
DIM UP/DOWN	ONE LONG PRESS
When paired with a light, long press button to dim up or down. Release button to stop.	
FULL BRIGHTNESS	2 PRESSES
When paired with a light, sets light to full brightness.	
DELAY TO OFF	3 PRESSES*
Paired device turns off automatically after a set time (configured in the app). Single click to cancel.	
VARIABLE	4 PRESSES*
Refer to the paired device for functionality.	
VARIABLE	5 PRESSES*
Refer to the paired device for functionality.	
PAIRING MODE	6 PRESSES
Pair a button with another KASTA device when prompted by the KASTA app.	
FACTORY RESET	9 PRESSES

9 clicks of any button, restores all settings back to factory.

*If successful, the blue LED indicator will flash rapidly then change to a slow, flash before entering sleep mode.

APP ENABLED FUNCTION

RETRIGGER TIMER	1 PRESS
-----------------	---------

Commence timer (on/off). Function must be programmed through the KASTA app first.

TECHNICAL SPECIFICATIONS

Operating Temp: 0°C to 40°C

Range: Up to 30m open air

Battery: CR2032 Lithium (x2)

Battery Life: 1 year

CONNECTION DIAGRAM

CONNECTION DIAGRAM

