


Installation Instructions



Smart Dimmer Mechanism

Product Code:
KASTA-1BMBH-W

APP Installation

Visit www.kasta.com.au or your app store to download the free KASTA app.
iOS: requires iOS 9.0 or later.
Android: requires Android 4.4 or later.
Devices must support Bluetooth 4.0



Important Safety Information

- This product must be installed by a licensed electrician in accordance with all the requirements of AS/NZS 3000 (current edition) and other relevant Standards and Regulations.
- Electricity MUST be disconnected prior to installation. Failure to do so may result in serious injury and or loss of life.
- Indoor use only. Not suitable for damp or explosive environments.
- Complies to Australian Standards AS/NZS 60950.1:2015, AS/NZS CISPR 15.
- No user serviceable parts inside.

FEATURES

- Mains powered one button remote switch mechanism.
- Simple 2 wire connection – A, N.
- Can be paired with KASTA dimmer and switch relay mechanisms for multi-way control (8x maximum).
- Short press for on/off control, long press for dimming control (default settings).
- Smart functions via phone/tablet with the app such as schedules, timers, scenes and groups.
- Fits most Australian Standard wall mech apertures.
- Integral blue backlight.
- To prevent a reduction in Bluetooth® signal strength, install away from metal objects.

FUNCTION SETUP

ON/OFF SWITCH	1 CLICK
Turns lights on or off. When turned ON, lights will adjust to previous brightness setting.	
DIM UP/DOWN	ONE LONG PRESS
When lights are on, long press button to dim up or down. Release button to stop. Only applicable when paired with Push Button Smart Dimmer or Hidden Smart Dimmer.	
FULL BRIGHTNESS	2 CLICKS
Sets lights to full brightness. Only applicable when paired with Push Button Smart Dimmer or Hidden Smart Dimmer.	
DELAY TO OFF	3 CLICKS*
Lights automatically turns off after set time.	
SET MIN DIM LEVEL	4 CLICKS*
Dim to desired level. Click button 4 times to store setting. Only applicable when paired with Push Button Smart Dimmer or Hidden Smart Dimmer.	
RESET MIN DIM LEVEL	5 CLICKS*
Restores back to factory minimum dimming level.	
FACTORY RESET	9 CLICKS
Restores all settings back to factory. *If successful, light will pulse the number of times that the switch was clicked, indicating function.	

APP ENABLED FUNCTION

RE-TRIGGER TIMER	1 CLICK
Enable delay to on/off. Function must be programmed through app first.	

TECHNICAL SPECIFICATIONS

Operating Temp: -20°C to 40°C

Supply: 220-240V AC 50Hz

CONNECTION DIAGRAM

